JAB Series

2 x 30 Watt Class D Audio Amplifier Board w DSP - JAB3

(AA-JA32473)

Key Features

- 3.60 x 2.70 Inches PCB Size
- Battery Board Supported*
- Power Management Circuit
- DSP Integrated
- Gain of Speaker Output Adjustable
- High-pass Filter of Speaker Output Adjustable
- High-pass Filter of 3.5mm
 Headphone Output Adjustable
- Overall Volume Adjustable
- Signal Level Sensor System*
- External 3.5mm AUX IN Port
- Power Switch Port*
- 3.5mm Headphone Output
- Compatible with JAB2*

Distributors:









All Audio Amplifier boards are complied with ROHS and they are pre-tested with our power supply solution to comply with FCC and CE. We could provide FCC, CE and RoHs certifications for customers' convenience. The test reports will be provided upon requests by e-mails only for customers who apply for bulky purchasement of MOV USD\$10,000 or MOQ 500pcs.

Ready for:



Contact Info

• Email:





Specifications typical @ +25°C, Powered by 24V DC, unless otherwise noted. Specifications subject to change without notice.

Paramete	er	Conditions	Min.	Тур.	Max.	Units
Number o	f Channels	-	-	2	-	-
Minimum	Load Impedance	-	3.2	4	- 1	Ω
Efficiency	•	2 x 30W @8Ohm, 1kHz	-	84	-	%
Nominal Po	ower Requirement	@24V, 1kHz	-	130	- 1	W
Operating	Voltage	@1kHz, 8Ohm	12	24	26	V
Idle Powe	_	Signal detected	-	2	- 1	W
idle Powe	I	No Signal detected	-	60		
Switching	Frequency	SD Floating@24V	-	400	- 1	kHz
Power Consumption		1/4 of max output power@8Ohm, 24V, 1kHz	-	20	-	W
Power Co	insumption	1/8 of max output power@8Ohm, 24V, 1kHz	-	10	-	W
	Standby	High-level Input Voltage	6.0	-	-	V
Control	(Low = inputs enabled)	Low-level Input Voltage	-	-	0.4	V
Control	Mute	High-level Output Voltage	3.5	-	-	V
	(High = outputs enabled)	Low-level Output Voltage	-	-	0.4	V
Standby Po	ower	SD short to GND, only when low power module available	-	120	-	mW
Jnder Volta	age Protection	-	10.0	10.4	10.8	V

Audio Performance

Specifications typical @ +25°C, powered by 24V DC, unless otherwise noted. Specifications subject to change without notice.

Parameter		Conditions	Min.	Тур.	Max.	Units
Amp Gain		@8Ohm, 20Hz - 20kHz	-	26	-	dB
DCD Cair	SE1 (Single Amp)	@8Ohm, 1kHz	-60	-	0	dB
DSP Gain	SE2 (Headphone)	@8Ohm, 1kHz	-60	-	6.5	dB
Input Sensitivity		2 x 30W@8Ohm, 1kHz, 26dB		770		mV
Filter Gain		Butterworth, Q= 0.707	-	4	-	dB
Cutoff Frequency	,	HFP	0.25	-	2	kHz
Cuton Frequency		LFP	-	20	-	kHz
SNR		2 x 30W@8Ohm, THD+N=1%, 26dB, A-weighting		88		dB
THD+N		5W@8Ohm, 1kHz, 24dB		0.04		%
I UD+IN		10W@8Ohm, 1kHz, 24dB		0.06		%
Input Impedance		-		10		kΩ
Supported Samp	ing Rates	-	-	48	-	kHz
Output Noise Lev	rel	A-weighting, Input Connected to GND, 26dB		260		uV
DC Offset		-		10		mV
Max output Level		J3, 3.5mm Headphone Output Connector		7.8		dBu
Crosstalk Separa	tion	20Hz-20kHz, Gain=26dB	-	-60	-	dB

***Notes:

- JAB3 can be powered by 3S18650 Lithium Battery Balance and Protection Extension Board (AA-JA11113), which
 is designed for protecting batteries and balancing voltage. Please kindly be noticed that the battery charging circuit
 is integrated in JAB1/2, which means that JAB1/2 is a requisite if you want to charge battery board.
- Sure Electronics will update the hardware of JAB2 to make it fully compatible with JAB3. This means, when using JAB3 with this version JAB2 (PCB Version: AA-JA13217V150), some compatibility problem, like popping noise, may occur but will not affect the normal use. For more information about JAB2, contact us at store@sure-electronics.com.
- 3. Signal Level Sensor System has been employed in JAB3 for low power consumption. JAB3 will enter into standby mode when audio signal is not detected for long time (1min). Once audio signal is detected under this circumstance, JAB3 will restart to work. It is not malfunction if JAB3 enters into standby mode.
- JAB3 can be connected with JAB2 through J5 port on JAB3 with a 6pin cable. This cable is provided in the Functional Cables Package for JAB3.
- 5. The basic cable package of JAB3 contains: one power cable, one speaker cable, one control cable and one 3.5mm AUX IN cable. If you have special requirements of cables, please contact us at store@sure-electronics.com.

All parameters were tested with Rohde & Schwarz UPV audio analyzer (AES17 filter enabled) and Audio Precision AUX0025 filter. For authorized distributors and OEM customers who need more detailed performance graphs and parameter settings, please send an inquiry e-mail to us. (Not available for retail customers)

Function of Potentiometers


Fund	Functions of potentiometers based on specific applications					
Port	Function	JAB3S	JAB3M	JAB3S+ JAB2	JAB3M+ JAB2	
POT1	CH1 Gain	Gain of Speaker Output	Gain of Speaker Output	Gain of Speaker Output of JAB3	Gain of Speaker Output of JAB3	
POT2	CH1 HPF or BPF	High-pass Filter of Speaker Output	Band-pass Filter of Speaker Output	High-pass Filter of Speaker Output of JAB3	Band-pass Filter of Speaker Output of JAB3	
РОТ3	CH2 HPF	High-pass Filter of 3.5mm Headphone Output	High-pass Filter of 3.5mm Headphone Output	High-pass Filter of Stereo of JAB2	High-pass Filter of Stereo of JAB2	
POT4	CH1 & CH2 Volume	Volume of Speaker & 3.5mm Headphone Output	Volume of Speaker & 3.5mm Headphone Output	Overall Volume of JAB3 & JAB2	Overall Volume of JAB3 & JAB2	


Note:

- 1. The speaker output (J10) of the board with potentiometers is defined as CH1; 3.5mm headphone output (J3) or other integrated circuit output of the board with potentiometers is defined as CH2.
- 2. JAB3S refers to JAB3 in stereo mode, namely 2 x 50 Watt Class D Audio Amplifier Board w DSP JAB3 (AA-JA32172) and 2 x 30 Watt Class D Audio Amplifier Board w DSP JAB3 (AA-JA32473); JAB3M refers to JAB3 in mono mode, namely 1 x 100 Watt Class D Audio Amplifier Board w DSP JAB3 (AA-JA31181) and 1 x 60 Watt Class D Audio Amplifier Board w DSP JAB3 (AA-JA31211).

 3. HPF refers to High-pass Filter; BPF refers to Band-pass Filter.
- When CH1 is stereo output, the function of POT2 is HPF; when CH1 is mono output, the function of POT2 is BPF.
- 4. Four applications are exampled in this datasheet. For the functions of potentiometers when used in other applications, please contact us at store@sure-electronics.com.


Function	Range of Frequency
High-pass Filter (Stereo Mode)	20Hz- 2kHz
High-pass Filter (Mono Mode)	250Hz- 2kHz
Band-pass Filter	60HZ-120Hz (High-pass)
Danu-pass Filler	200Hz-400Hz (Low-pass)





Adjustable Range of Upper Frequency of Band-pass Filter

Mechanical Dimensions



Dimensions A (inch/mm) A1 (inch/mm) B (inch/mm) B1 (inch/mm) D (inch/mm) 3.60/91.44 3.30/83.8 2.70/68.6 2.40/61.0 0.14/3.6

Notes:


- \cdot All dimensions are typical in inches/mm
- Tolerance $x.xx = \pm 0.02(\pm 0.50)$

DSP Extension Port:

J2, PH- 10Pin- 2mm

Pin	Definition	Pin	Definition
1	GND	6	MP00
2	DATA	7	MP01
3	LRCLK	8	MP05
4	BCLK	9	MP04
5	MP07	10	+3.3V

Connections



Programming Connector:

·J4, PH- 6Pin- 2mm

- ·, · · · · - · · · - · · · · ·			
Pin	Definition	Pin	Definition
1	SDA	4	GND
2	SCL	5	VIN
3	WP	6	RST

Power Supply Connector:

J9, Molex- 2Pin- 3mm

,	
Pin	Definition
1	VCC
2	GND

Switch Control Connector*:

J12, PH- 3Pin- 2mm

Pin	Definition
1	STBY
2	GND
3	MUTE

Audio Output Connector:

- ·J10, Speaker Output Connector
- ·J3, 3.5mm Headphone Output Connector

Audio Extension and Compatible Port:

J5, PH- 6Pin- 2mm

Pin	Definition	Pin	Definition
1	LIN	4	GND
2	LOUT	5	ROUT
3	GND	6	RIN

Extension Connector:

-J6, PH- 10Pin- 2mm

Pin	Definition	Pin	Definition
1	VCC	6	LIN
2	VCC	7	GND
3	GND	8	RIN
4	LED1	9	KEY2
5	KEY1	10	LED2

Battery Board Connection Connector:

·J8, PH- 4Pin- 2mm

·30, F11- 4F111- ZIIIIII					
Pin	Definition	Pin	Definition		
1	VBAT	3	GND		
2		4	GND		

*Notes:

- 1. Short circuit 'STBY' and 'GND' to enter into 'Standby' mode.
- 2. Don't short circuit 'MUTE' and 'GND' at any time. This position is used to synchronize with 'MUTE' pin on JAB2 to eliminate the popping noise.
- 3. When JAB3 is used separately, the 'MUTE' position will malfunction; when JAB3 is used together with JAB2, J12 must be connected with the 3pos control port on JAB2 for controlling the whole system. Short circuit 'EN' with 'GND' on JAB2 for system control.

Sure Electronics

Make Your Audio Application Simple!

NO.9, Weidi Road, Xianlin University City, Qixia District, Nanjing, Jiangsu Province, P.R.C

www.sure-electronics.com www.wondom.com

Mail: store@sure-electronics.com Skype: surewebstore

